

Also available

S-board 840 Compact Keyboard

- Comes with multimedia keys and 2 USB ports (USB hub)
- Optimal layout: extra wide space-bar and user-friendly positioned arrow keys
- Mobile: only 2 cm thick and lightweight
- Ergonomic: pleasurable typing feeling (scissor mechanism instead of membranes)
- USB connection

Specifications

- Product code: BNES840D* (*=lay-outs: US, UK, DE, BE, FR)
- Dimensions: 305 x 165 x 20 mm
- Weight: 480 g




BakkerElkhuizen

Taalstraat 151
5261 BC Vught
The Netherlands
tel. +31 36 546 7265
fax. +31 36 546 7830
email. info@bakkerelkhuizen.com

All rights reserved. All trade names are registered trademarks of the respective manufacturers listed. All specifications are subject to change without prior notice.

www.bakkerelkhuizen.com

BakkerElkhuizen S-board 840 Numeric Keypad User Manual





User's Manual S-board 840 Numeric Keypad

- SEND** > Send the calculation result to host computer
- MR** > Transfer content of memory register to display
- MC** > Clear the memory
- PC/CAL** > Switch between Keypad mode and calculator mode when connected to computer
- CE/AC** > **Keypad/calculator mode**
After 10 minutes the keypad automatically goes to a sleep mode, to save energy. To restart working push this button
- Calculator mode**
Set display to '0' and after making digit entry it clears the entry register
- M+** > Add the result in the display to the memory
- M -** > Subtract the result display from the memory
- > **Keypad mode**
Back space function
- Calculator mode**
Delete the far right digit by shifting the display value to the right

Quick starting guide

1. Connect the keypad to one of the USB ports of your computer.
2. After the hardware is found: Turn the Numeric Keypad on, by pressing the 'CE/AC' button.



! To extend the life of the S-Board 840 numeric, we recommend that you use the supplied case when you store your S-Board 840 numeric.